#### **16-port SOHO Fast Ethernet switch, Plug and Play** Live-16E





Fast Ethernet 16-Port RJ45

Plug & Play

Light Weight

Surge / ESD protection

## **Overview**

## Plug-and-Play 16-Port Fast Ethernet Switch

Designed as plug-and-play unmanaged Fast Ethernet switch, AirLive Live-16E switch is equipped with 16 x 10/100Mbps RJ45 ports at very affordable price. Moreover, The Fast Ethernet switch is easy to manage and maintain with its fan less design and small size, the product can be widely used in home, SOHO office, or as client switch for SMB.



# **Features**

- 16 x 10/100Mbps RJ45 Fast Ethernet Switching ports
- Surge / ESD protection
- Tiny Lightweight
- Plug & Play

# Specification

# airlive

#### Model

#### Hardware

- Device Interface: 16 x 10/100Mbps RJ45, Auto MDI/MDI-X
- Standard IEEE802.3 Base-T IEEE802.3u 100Base-TX IEEE802.3x
- Industry standard compliant CE, ROHS
- LED Indicators:
  PWR (power supply), Link (Network Link)
- Lighting Surge Protection: IEC61000-4-2 (ESD), IEC61000-4-5(Surge) Power:CM±4kV/DM±2kV; Port: ±4kV , ESD: ±8kV Contact discharge, ±15kV Air discharge
- Mechanical Plastic

#### Switch Architecture | Performance

 Switching architecture: Store and Forward Switch Capacity: 3.2Gbps Throughput; 2.38Mpps MAC Address: 8K Packet Buffer: 2M Transfer mode: Store and forward

#### AirLive Live-16E

#### Power Supply

Power Supply: DC5V1A External power adapter

#### Environment

- **Operating Temperature:** 0°C~+40°C
- Storage Temperature: -40°C~+70°C
- **Operating Humidity**: 10%~90%, non-condensing
- Storage Humidity: 5%~95%, non-condensing

#### Standard package of switch

- **Product size:** 14 x 10.5 x 3.5 cm
- **Package size:** 16 x 11 x 7 cm
- Product Weight/Package Weight G.W: 0.36kgs
- Package content: 1 x Switch, 1 x Power Adapter

#### Standard carton package

- Quantity: 50 pcs / 1 carton
- Dimensions 67.5 x 33.5 x 36 cm
- Carton Weight 19.2Kgs

#### **Ordering Information**

- Model: <u>Live-16E</u>: 16 x 10/100Mbps RJ45 Switch
- Name: 16-port Fast Ethernet Switch, Plug and Play

AirLive

\* Specification will be changed without prior notice